

## **CCD\*\*\*** Digital Control Module





Works with 5T650BODE Trunk Amp for BODE Operation from Single Pilot

## **Works with a Digital or Analog Channel**

First Operational Digital Keyed AGC

**Patent Pending** 

**Helical Filters** 

**Specifications in Housing** 

| Parameter             | <b>Test Conditions</b>    | Units | Notes | Forward           |      |
|-----------------------|---------------------------|-------|-------|-------------------|------|
| Modulation            | -                         | -     | 1     | Analog or Digital |      |
| Frequency             | -                         | MHz   | -     | As Ordered        |      |
| Pilot Levels          | -                         | dB    | -     |                   |      |
| Analog                | At CCD input Pilot 505.25 | dBmV  | 2     | 18                |      |
| Digital               | Pilot at 507 MHz          | dBmV  | 3     | 12                |      |
| Recovery Performance  | ± 3                       | dB    |       |                   |      |
| Constant Temperature  |                           | dB    |       | ±                 | 0.75 |
| -40 F to +140 F       |                           | dB    |       | =                 | ± 1  |
| DC Current Draw (max) | -                         | mA    | -     |                   | 80   |

843-365-4938

## **Notes:**

- 1. Digital levels are assumed to be 6 dB down from Analog
- 2. All units are aligned for operation with an Analog channel with a 3 dB pad in the unit..
- 3. For operation with a digital channel the 3 dB pad must be replaced with a 0 dB pad.

Available now from stock to 4 weeks

Contact: 4Cable TV Inc.

4254 Highway 501 West Conway SC 29526

www.4cable.tv sales@4cable.tv